

MyE Programming



1. Press Power Button



2. Press and hold **CHANNEL DOWN** and **VOLUME UP**



3. Until P-1 shows up



5. It is going to scroll to all the possible channels in your location (It is completed when its default back to 1)

NOTE: IF THE SIGNAL IS TOO WEAK YOU HAVE TO MANUALLY ENTER THE CHANNELS BY PRESSING THE TV BUTTON FOR EACH CHANNEL.



6. If you don't see the word **PRESET** on the screen, Press the **TV** button until you see **PRESET** on the screen.



7. Use the **CHANNEL ARROW UP** button to verify all the correct channels are **PRESET**. (Press TV Button to get erase the **PRESET** status) NOTE: Y



8. Once you have the correct channels **PRESET** hit the Key **PROGRAM**



9. Send the information to the console by pressing **PROGRAM** and **SEND** together



10. The message **Snd** confirms the unit is in **SEND MODE**

NOTE: VERIFY AUDIO WITH HEADPHONES BETWEEN STEPS 7 & 8

Consoles C and X Go To Next Page



11. Send the information to the console by pressing **PROGRAM** and **SEND** together



12. The **number 1** in the screen means the unit is programmed.



1. Create the channel listing on the MYE programming remote to 1 channel. (see link at the bottom of this page)
2. Place MYE Programming USB into console USB port
3. While in SEND mode on the programmer, Point remote sensor at the USB Stick and press SEND. The left side of the USB stick will blink indicating that it's receiving the channel listing from the remote. Once the blinking stops, the channel listing has been uploaded to the USB Stick.
4. With the MYE USB stick in place, begin the download sequence by pressing R-UP, R-Down, R-UP, R-Down, TIME.
 - a. If a check mark appears, it means it's successful. Move on to 7.
 - b. If an X appears, repeat steps validate that you only get 1 channel
5. Validate that MYE program channel list has been uploaded on console. Also check for sound. It should only be 1 channel
 - a. If successful, move to step 8
 - b. If not successful repeat steps 1-7.
 - i. If still unsuccessful, open console to check MYE receiver version. If it is MLF2-C93. Escalate to Engineering
6. Reprogram the MYE receiver to the correct channel listing (Concord has 10 Channels). Follow steps 3-7
7. Once the correct channel listing is uploaded, validate